Pure Sine Wave DC to AC Power Inverter - P Series

Inverter Expert P3000U-3000W with USB

Quality

- Features: ■
- Input & output fully isolated. ◀
 - With USB output port <
- High Surge: High surge current capability starts difficult loads such as TVS, ◀ camps, motors and other inductive loads.
 - **Soft start:** Smooth start-up of the appliances. ◀
 - Pure Sine Wave Output Waveform: Clean power for sensitive loads. ◀
- AC output identical to, and in some cases better than the power supplied by your utility. ◀
 - Cooling Fan: Control by load or temperature (optional)
 - Low Total Harmonic Distortion: below 3% ◀

Remote Control: optional

AC Output Recepatacles(optional)













						_	_		-
		₩:>	400					(°)	
	В		D	E		G			GFCI
USA	AUSTRALIA	UNIVERSAL	Europe+USA+Japan	U.K	FRANCE	GERMANY	BRAZIL	ISRAEL	USA-GFCI

■ SPECIFICATION:

	MODEL	P3000U-121	P3000U-241	P3000U-481	P3000U-122	P3000U-242	P3000U-482			
	AC VOLTAGE		100/110/120VAC			220/230/240VAC				
	RAT ED POWER	3000W								
	SURGE POWER	6000W(for few seconds)								
	USB	5V,500mA(optional)								
OUTPUT	WAVEFORM	Pure Sine Wave(THD<3%)								
	FREQUENCY	50/60Hz ±3Hz								
	AC REGULATION									
	STANDARD RECEPTACLES									
	LED INDICATOR	A, B, C, D, E, F, G, H, I, GFCI (optional as above) Green for power on, red for failure or protection status indication								
	NO LOAD CURRENT DRAW	≤1.6A								
	DC VOLTAGE	12V	24V	48 V	12V	24V	48 V			
INPUT	VOLTAGE RANGE	10.5~15.0VDC	21.0-30.0V DC	42~60V DC	10.5~15.0VDC	21.0-30.0V DC	42~60V DC			
	EFFICIENCY (Typ.)	>87.0%	>90.0%	>90.0%	>87.0%	>90.0%	>90.0%			
	FUSE	50A*6	25A*6	15A*6	50A*6	25A*6	15A*6			
	DC CABLE (60CM)	BVR4*6	BVR4*4	BVR4*6	BVR4*6	BVR4*4	BVR4*6			
	BAT.LOW ALARM	11±0.5V DC	22±1VDC	44±2V DC	11±0.5V DC	22±1VDC	44±2V DC			
	BAT.LOW SHUTDOWN	10.5±0.5V DC	21.0±1VDC	42±2V DC	10.5±0.5V DC	21.0±1V DC	42±2V DC			
	OVERLOAD	Shutdown								
entale Malaini et attoriolo	OVER VOLTAGE	14.8±0.5V DC	29.6±1V DC	58.4±2V DC	14.8±0.5V DC	29.6±1V DC	58.4±2V DC			
PROTECTION	OVERTEMPRETURE		Shut-off output v	rature goes down						
	SHORT CIRCUIT	Shut-off output voltage, repower on to recover								
	BAT.REVERSE POLARITY									
	SOFT START	By fuse open Yes 5~10s								
	GROUNDING PROTECTION			es						
NVIRONMENT	RESET VOLTAGE AFTER LVS	11.8~12.8VDC	23.6~25.6V DC	47.2~51.2V DC	11.8~12.8VDC	23.6~25.6V DC	47.2~51.2V D			
	WORKING TEMP.	0-40℃								
	WORKING HUMIDITY	20%-90% RH non-	condensing							
	STORAGE TEMP.& HUMIDITY	· ·					Turbo			
	SAFETY STANDARDS	UL458(only for Gl	Soft High Start Efficiency Cooling fan							
	ISOLATION RESISTANCE	X								
SAFETY	EMI CONDUCTION & RADIATION	Compliance to EN.	55022 Class A			Universal Protecti Circuit	Ownied Ownied Start threat Own-temperature			
& EMC	EMS IMMUNITY	Compliance to EN	61000-3-2, 3	On continue						
	LVD	Compliance to EN	60950-1: 2006+A11:2	Compact Design						
	E- MARK	Compliance to E8*	*72/245/EEC, 95/54/I	Compact Des	1811					
	REMOTE CONTROL	Switch with 5m wi	re (optional)		r					
	DIMENSION	460*230*108mm		L.I.T Low Interference Technology						
	PACKING	7Kg, 2pcs/19.5Kg	s/Ctn(46*31.5*38.5cm							
OTHERS	COOLING FAN	Control by load/ter	mperature(optional)	USB 5V == 500m A						
	APPLICATION	Home and office app	pliances, Power tools ar	USB 5V 500IIIA						
INSTALL	ATION	PURE SINE	, AC LOAD—			100% pure sine	y Solution Mobile AC Source wave output, public power.			